

# Kronzilla VA830

Stereo integrated amplifier. 40 + 40 Watts RMS

<b>Power Tube</b>	4 x KR300B
<b>Output Power</b>	2 x 60 WRMS (THD=1%)
<b>Output</b>	4,8 $\Omega$
<b>Frequency Response</b>	20Hz ÷ 45KHz (-3dB)
<b>Feedback</b>	Zero
<b>Driver stage</b>	Mosfet class A
<b>Preamplifier</b>	Solid state with mecanical (reed) relay
<b>Remote control</b>	volume & channel selector
<b>Inputs</b>	4 x line RCA (Cinch)
<b>Power requirements</b>	230/115VAC, 50/60 Hz
<b>Power consumption</b>	250VA
<b>Operating temperature</b>	5C° to 40C°
<b>Weight</b>	Approx. 50Kg
<b>Dimensions</b>	Approx. 38,5 x 24,5 x 41,5 cm
(including projecting parts and controls (w/h/d))	

